



THURAYA FDU XT



Fixed docking unit for Thuraya XT,
XT Pro and XT Dual



**ENABLES INDOOR USE OF
SATELLITE PHONES**

**COMPLEMENTS THURAYA
XT, XT DUAL AND XT PRO
SATELLITE PHONES**

**CHARGES A DOCKED
SATELLITE PHONE**

**SUPPORTS GROUP 3
ANALOGUE FAX
MACHINES AND PC FAX**

**FACILITATES SEAMLESS
CIRCUIT-SWITCHED
DATA SERVICE AT
SPEEDS UP TO 9.6 KBPS**



The FDU-XT is a home and office docking adapter that allows you to use the Thuraya XT, XT Pro and XT Dual phones in an indoor setting. Simply connect the FDU-XT to the antennas; then, dock the Thuraya handset into the cradle, and start to enjoy satellite phone connectivity. Easy to install and operate, it supports Voice, Data, and Fax transmissions, and comes with SAT and GPS antennas and 25m cables to ensure seamless connectivity.

KEY FEATURES

- Easy to install and operate
- Compatible with Thuraya XT Satellite Phones
- Supports
- High-quality voice transmission via auxiliary handset, speakerphone or any analogue extension telephone
- Charges a Thuraya XT satellite phone while docked in the cradle
- Supports GMPRS services with USB port or DTE
- Supports circuit switched data service at speeds up to 9.6 kbps
- Supports PABX connection

SPECIFICATIONS:

Dimensions: 221 x 176 x 80 mm

Interfaces

- 3 RJ-11:
 - External telephone connection (voice call)
 - External G3 fax connection (fax call)

- Auxilliary handset connection (voice call)
- 1 x RS-232 serial connection
- 1 x USB PC connection
- 2 x SMA connectors:
 - Satellite antenna connection
 - GPS antenna connection

Power

- Universal AC/DC power supply 110-240V
- Input power DC 12V/24V/34V

PACKAGE CONTENTS

- FDU-XT main unit
- Auxiliary handset
- SAT antenna with 25m cable
- GPS antenna with 25m cable
- Mounting kit
- Universal power supply (Input: 100-240V AC, Output: 12V DC)
- USB cable
- RJ-11 cable
- Support CD
- User manual